
7SEGP120

Processor: 68HC05C8A

Target Display: 228/406

Description: serial output must be polled - it is not automatic.

To poll, send ^B<AA>P^C - where <AA> is the address if the unit (if set to addressable, otherwise leave blank). ^B = STX; ^C = ETX; P = character P

It will return ^B<AA><NNNN>^C with the result, <AA> if addressable is setup.

Control Bd: 1700-402

Baud Rate In: 1200

Baud Rate Out: 1200

Input Protocol: $\text{<STX><ADD><ADD><P><ETX>}$

Output Protocol: $\text{<STX><ADD><ADD><actual display reading><ETX>}$
